

FP-1b/FP-2b



SPECIFICATIONS	FP1b	FP2b
LCD indicator	3 1/2	3 1/2
DC voltage	200mV, 2V, 20V, 200V, 1000V	200mV, 2V, 20V, 200V, 1000V
AC voltage	2V, 20V, 200V, 750V	2V, 20V, 200V, 750V
DC current	2mA, 20mA, 200mA, 10A	2mA, 20mA, 200mA, 10A
AC current	2mA, 20mA, 200mA, 10A	20mA, 200mA, 10A
Resistance	200 Ω , 2 k Ω , 20 k Ω , 200 k Ω , 2 M Ω , 20 M Ω	200 Ω , 2 k Ω , 20 k Ω , 200 k Ω , 2 M Ω , 20 M Ω , 200 M Ω
Diode Test	Yes	Yes
Continuity audible	Yes	Yes
Overload input protector	Yes	Yes
Capacitance	-	2 nF, 20 nF, 200nF, 2 μ F, 20 μ F
Frequency test	-	2kHz, 20kHz
h_{FE} de transistors	-	Yes
Battery test	Yes	-
Auto power off	-	Yes
Basic accuracy	$\pm(0.5\% \text{ read} + 1 \text{ digit})$	$\pm(0.5\% \text{ read} + 1 \text{ digit})$
Maximum voltage	1000 V DC / 750 V AC	1000 V DC / 700 V AC
Protection	By fuse	By fuse

MULTIMETER ACCESSORIES

1) SV-013	40 kV CC high voltage probe
2) SD-014	RF 800 MHz detection probe
3) PP-008	Elbow-shaped test leads for PD multimeters
4) CA-4000	100 A AC current clamp
5) PP-009	SMD test leads
6) DC-281	Holster for PD-984 / PD-986
7) DC-213	Carrying case

